AC191 Terminal Block Mounted on the Bearing Shoe

Contents

Contents of the AC191 package:

• Terminal block



Reference Documents

Install the temperature detector according to the appropriate procedure. See table below for the correct Installation Instruction.

| Installation Instruction | Case Style | Case Diameter | Method of Installation |
|---------------------------|------------|--|--------------------------|
| II #164 (formerly El 164) | А | 0.275" (7 mm) | Babbitt (Sleeve Bearing) |
| II #167 (formerly El 167) | А | 0.275" (7 mm) | Babbitt (Thrust Bearing) |
| II #180 (formerly EI 180) | В | 0.188" with 0.250" φflange (4,75 mm with 6,35 mm φflange) | Babbitt (Thrust Bearing) |
| II #181 (formerly EI 181) | В | 0.188" with 0.250" φflange (4,75 mm with 6,35 mm φflange) | Spring and Ring |
| II #184 (formerly EI 184) | C & D | 0.125" & 0.080" (3,20 mm & 2,05 mm) | Potting |

Procedure

Follow the procedure below to mount the AC191 Terminal Block on the bearing shoe. This procedure is adaptable to other types of bearings and to equipment other than bearings.


| Step | Action |
|------|---|
| 1 | Drill or counterbore a 0.625 " $\pm .005$ " (15,9 mm ± 13 mm) diameter hole, .1875" deep, in the bearing shoe at the desired location. The terminal block may be located adjacent to the detector leadwire hole, and must be mounted within the leadwire length of the detector being installed. |
| 2 | Insert the terminal block in the 0.625" (15,9 mm) diameter hole with the leadwire grooves aligned with the direction the leadwires will lay. |
| 3 | Peen over the metal of the shoe into the recess in each quadrant of the terminal block to hold the terminal block securely in place. |
| 4 | Form the stripped and tinned ends of the detector leadwires into the solder cups of the terminal block. Do the same with the leadwires exiting the terminal block. Solder the leadwires into the solder cups with 60/40 alloy solder (for use to 360°F (182°C)) or higher temperature solder if service conditions require. |
| 5 | Lay the leadwires flat in the bottom of the milled groove in the bearing shoe. Pot the leadwires in the groove using an epoxy or other potting compound compatible with the bearing shoe material, temperature and service conditions |


Continued on next page


AC191 Terminal Block Mounted on the Bearing Shoe, Continued


Drawing

See the drawing below for the suggested installation procedure.









SUGGESTED STAKING TOOL FOR INSTALLING TERMINAL BLOCK MODEL AC191

www.minco.com